

EM-W481

WEICHAI Engine



Generator Specification

Service	PRP	ESP
Power (kva)	438	482
Power (kw)	350	385
Rated speed (r.p.m)	1800	
Rated Power factor	0.8 @lagging	

Performance

Engine Brand	WEICHAI
Engine model	WP13D460E311/418KW
Alternator	VG-314F/384KW
Breaker	CHNIT MCCB 3P
Control system	AMF digital panel
Fuel consum. @100% load	195 g/kW.h

CERTIFICATE:

EMEAN Power gensets are compliant with ISO 9001 and CE standard, which include the following directives: EN ISO 12100:2010, EN ISO 8528-13:2016, EN 60204-1:2006+A1:2009+AC:2010, EN 55012:2007+A1:2009




CERTIFICATE:

EMEAN Power gensets are compliant with ISO 9001 and CE standard, which include the following directives: EN ISO 12100:2010, EN ISO 8528-13:2016, EN 60204-1:2006+A1:2009+AC:2010, EN 55012:2007+A1:2009

Dimension

Type	Open	Silent
Length (L)	3510mm	4100mm
Width (W)	1300mm	1600mm
Height (H)	2000mm	2250mm
Net Weight	4350kg	5200kg



Standard Features:

1. power by Brand new water cooled diesel engine
2. Brushless alternators (Class H, with AVR)
3. Working condition: 0°C ~ +40°C (Antifreeze system needed if below 0°C)
4. Base frame fuel tank for continue 8-10hrs running
5. Digital control panel with auto protection
6. MCCB air circuit breaker for over current shutdown
7. Industrial silencer for silent type generator sets
8. Humanized design, simple operation, easy maintenance
9. Ventilation parts are designed with modular principles
10. Soundproof canopy which lined with sound reducing foam
11. All metal canopy parts are painted by powder foam
12. Glass Panel window
13. Lockable doors on front and back side for easy maintenance
14. Easy maintenance and operation
15. Easy lifting and moving, there is forklift hooks and crane holes on chassis
16. External emergency stop button
17. Steel chassis and anti-vibration pads
18. Includes diesel level sensor information to the controller




Warranty

We shall provide a warranty of 12 months or 1200 hours from B/L date (whichever comes first), covering all manufacturing defects. We replace damaged parts caused by manufacturing faults or defected parts/materials, but exclude the damageable parts due to customer's incorrect man-made operation. After expiration, we still provides technical and spare parts support with cost for maintenance.

Equip With

WEICHAI WP13D460E311/418KW

Please download the detailed engine data sheet



Alternator VG-314F/384KW

Please download the detailed alternator data sheet



Digital control panel

Please download the detailed controller manual



AUTOMATIC SHUTDOWN AND FAULT CONDITIONS

- Under/over speed; fail to start
- High engine temperature; fail to stop
- Low oil pressure; charge fail
- Under/over generator volts; over current
- Under/over generator frequency; emergency stop
- Under/over mains frequency
- Under/over mains voltage
- Low/high battery volts

CHNIT MCCB breaker 3P



Sealed 12/24V Dry battery



Option

ATS



Remote Control



Charger



Jacket Heater



Oil Heater



Extra Fuel Tank



Parallel Cabinet



Trailer



Contact Information

Email: sale5@fjepos.com

Phone: +86 19890349907

WHATSAPP



WECHAT



VIBER

