

EM3500

Gasoline Generator

EMEAN
POWER

TECHNICALS SPECIFICATIONS

Model:

EM3500

Gen set composed of engine and alternator perfectly assembled and fitted in a practical tubular chasis, that is adding great strenght and versatility.

Genset General Characteristics

Prime Power:	50HZ/2.5KW	60HZ/2.8KW
Standby power:	50HZ/2.8KW	60HZ/3.3KW
DC Output:	12V-8.3A	
Voltage:	110V/220V、115V/230V、 120V/240V、127V/220V、 220V/380V、230/400V、 240V/415V	
Fuel Tank Capacity:	13L	
Fuel Consumption:	≤1.55L/h / ≤1.75L/h	
Noise Level at 7M:	63~66dB(A)	
Product Dimensions:	590*450*440 MM	
Packing Dimension	600*460*460 MM	
N.W/G.W:	42KG/45KG	

OPTIONS

- Electric Start
- ATS
- Digital Meter
- Handles & Wheels
- Socket Style



Engine

Model:	170F
Fuel:	Gasoline
Cooling System:	Air
Type:	V-twin/L-single、4-cycle
Bore x Stroke:	70*54MM
Displacement:	0.210L
Compression Ratio:	20:01
Engine Speed:	50HZ/3000RPM 60HZ/3600RPM
Rated Output:	50HZ/4.3KW 60HZ/4.7KW
Combustion System:	Crystal Ignition
Starting System:	Recoil Start / Electric Start
Lube Oil Capacity:	0.6L
Lubrication Oil:	CD Grade Or Higher (SAE10W/30/SAE15W/40)

Alternator

Type:	Self Excitation、Constant Voltage、Field Rotating、 2 Pole
Phase:	Single Phase/3-Phase
Power Factor:	cOsφ 1.0/0.8
Insulation:	H
Portection Degree:	IP21

EMEAN POWER

www.emeanpower.com
Email: sale5@fjepos.com
Phone: +86 19890349907

WHATSAPP



WECHAT

